


## Instructions for use

## BLOOM! Ø 44 cm

### NOTE!

Only use G4 12-Volt halogen bulbs, **max. 10 watt** to prevent heat from building up in the planter

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors. The BLOOM! power cord must be led through the designated ducts.

Make sure that BLOOM! is placed on a stable surface. BLOOM! may not be embedded in the ground but should be placed at ground level. The same applies to the power cord and the adapter.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. The bulbs are hot, so wait a few minutes until they have cooled down.
3. Unscrew the lid.
4. Take the blown bulbs carefully out of the fitting. Do not tug or jiggle them as the feet may break off.
5. Press the new bulbs (**G4 12 Volt, max. 10 watt**) gently into the fitting, again without jiggling. Do not touch the bulbs as this will reduce their useful life. Use a piece of paper or the packaging material.
6. Screw the lid on tightly.
7. Put the plug into the socket again.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

The power cord cannot be replaced by the user because of the adapter. It has to be replaced entirely with a specially prepared cord complete with adapter supplied by the manufacturer.

### Technical specifications

#### Adapter:

Primary voltage	230V ~ 50 Hz
Secondary voltage	12V ~ 50 Hz / 3A
Capacity	36 VA
Protection class	Class 2
Protection grade	IP46
Cord	H05RN-F 2x1.00 with moulded plug(s)
Cord length	600 cm (total)

#### Planter:

Voltage	12V / 2A
Bulbs	G4 12 Volt, max. 10 Watt
Protection class	Class 3
Protection grade	IP44

#### Dimensions:

Diameter	44 cm
Height	40 cm
Weight	± 10 kg (including light bulbs and cord)

## Instruction for use

## BLOOM! Ø 66 cm

### NOTE! USE ONLY 11 WATT MAX. ENERGY-SAVING LIGHT BULBS

To prevent heat from building up in the planter.

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors, as long as you use earthed wall sockets. The BLOOM! power cord must be led through the designated ducts. Make sure that BLOOM! is placed on a stable surface at ground level and not embedded in the ground. The same applies to the power cord. Please see 'permanent configuration' if you do want to conceal the cord.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. Unscrew the lid.
3. Replace the light bulb(s), using only **11 watt max. energy-saving light bulbs**
4. Screw the lid on tightly.
5. Put the plug into the socket again.

### Permanent configuration

If BLOOM! is permanently installed outdoors (for more than one year), BLOOM! should be fitted with a suitable outdoor underground cord by a certified electrician.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. If the power cord is damaged, it should be replaced immediately by the same type of cord with a moulded plug. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

### Technical specifications

Voltage	220-240V~ 50/60 Hz
Protection class	Class 1
Protection grade	IP44
Light bulbs	2 x E27 (large socket) 230V <b>11 watt max. energy-saving light bulbs</b>
Cord	H05RN-F 3x1.00 with moulded plug

### Dimensions:

Diameter	66 cm
Height	60 cm
Cord length	400 cm
Weight	± 10 kg (including light bulbs and cord)

## Instruction for use

## BLOOM! Ø 99 cm

### NOTE! USE ONLY 18 WATT MAX. ENERGY-SAVING LIGHT BULBS

To prevent heat from building up in the planter.

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors, as long as you use earthed wall sockets. The BLOOM! power cord must be led through the designated ducts. Make sure that BLOOM! is placed on a stable surface at ground level and not embedded in the ground. The same applies to the power cord. Please see 'permanent configuration' if you do want to conceal the cord.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. Unscrew the lid.
3. Replace the light bulb(s), using only **18 watt max. energy-saving light bulbs**
4. Screw the lid on tightly.
5. Put the plug into the socket again.

### Permanent configuration

If BLOOM! is permanently installed outdoors (for more than one year), BLOOM! should be fitted with a suitable outdoor underground cord by a certified electrician.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. If the power cord is damaged, it should be replaced immediately by the same type of cord with a moulded plug. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

### Technical specifications

Voltage	220-240V~ 50/60 Hz
Protection class	Class 1
Protection grade	IP44
Light bulbs	2 x E27 (large socket) 230V <b>18 watt max.</b> energy-saving light bulbs
Cord	H05RN-F 3x1.00 with moulded plug

### Dimensions:

Diameter	99 cm
Height	90 cm
Cord length	400 cm
Weight	± 25 kg (including light bulbs and cord)

## Instruction for use

**BLOOM! Ø 110 cm**

### NOTE! USE ONLY 20 WATT MAX. ENERGY-SAVING LIGHT BULBS

To prevent heat from building up in the planter.

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors, as long as you use earthed wall sockets. The BLOOM! power cord must be led through the designated ducts. Make sure that BLOOM! is placed on a stable surface at ground level and not embedded in the ground. The same applies to the power cord. Please see 'permanent configuration' if you do want to conceal the cord.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. Unscrew the lid.
3. Replace the light bulb(s), using only **20 watt max. energy-saving light bulbs**
4. Screw the lid on tightly.
5. Put the plug into the socket again.

### Permanent configuration

If BLOOM! is permanently installed outdoors (for more than one year), BLOOM! should be fitted with a suitable outdoor underground cord by a certified electrician.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. If the power cord is damaged, it should be replaced immediately by the same type of cord with a moulded plug. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

### Technical specifications

Voltage	220-240V~ 50/60 Hz
Protection class	Class 1
Protection grade	IP44
Light bulbs	2 x E27 (large socket) 230V <b>20 watt max.</b> energy-saving light bulbs
Cord	H05RN-F 3x1.00 with moulded plug

### Dimensions:

Diameter	110 cm
Height	100 cm
Cord length	400 cm
Weight	± 25 kg (including light bulbs and cord)

## Instruction for use

## BLOOM! COLUMNS Ø 40 cm

### NOTE! USE ONLY 18 WATT MAX. ENERGY-SAVING LIGHT BULBS

To prevent heat from building up in the planter.

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors, as long as you use earthed wall sockets. The BLOOM! power cord must be led through the designated ducts. Make sure that BLOOM! is placed on a stable surface at ground level and not embedded in the ground. The same applies to the power cord. Please see 'permanent configuration' if you do want to conceal the cord.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. Unscrew the lid.
3. Replace the light bulb(s), using only **18 watt max. energy-saving light bulbs**
4. Screw the lid on tightly.
5. Put the plug into the socket again.

### Permanent configuration

If BLOOM! is permanently installed outdoors (for more than one year), BLOOM! should be fitted with a suitable outdoor underground cord by a certified electrician.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. If the power cord is damaged, it should be replaced immediately by the same type of cord with a moulded plug. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

### Technical specifications

Voltage	220-240V~ 50/60 Hz
Protection class	Class 1
Protection grade	IP44
Light bulbs	2 x E27 (large socket) 230V <b>18 watt max.</b> energy-saving light bulbs
Cord	H05RN-F 3x1.00 with moulded plug

### Dimensions:

Diameter	40 cm
Height	70 cm
Cord length	400 cm
Weight	± 9 kg (including light bulbs and cord)

## Instruction for use

## BLOOM! COLUMNS Ø 50 cm

### NOTE! USE ONLY 18 WATT MAX. ENERGY-SAVING LIGHT BULBS

To prevent heat from building up in the planter.

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors, as long as you use earthed wall sockets. The BLOOM! power cord must be led through the designated ducts. Make sure that BLOOM! is placed on a stable surface at ground level and not embedded in the ground. The same applies to the power cord. Please see 'permanent configuration' if you do want to conceal the cord.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. Unscrew the lid.
3. Replace the light bulb(s), using only **18 watt max. energy-saving light bulbs**
4. Screw the lid on tightly.
5. Put the plug into the socket again.

### Permanent configuration

If BLOOM! is permanently installed outdoors (for more than one year), BLOOM! should be fitted with a suitable outdoor underground cord by a certified electrician.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. If the power cord is damaged, it should be replaced immediately by the same type of cord with a moulded plug. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

### Technical specifications

Voltage	220-240V~ 50/60 Hz
Protection class	Class 1
Protection grade	IP44
Light bulbs	2 x E27 (large socket) 230V <b>18 watt max.</b> energy-saving light bulbs
Cord	H05RN-F 3x1.00 with moulded plug

### Dimensions:

Diameter	50 cm
Height	90 cm
Cord length	400 cm
Weight	± 20 kg (including light bulbs and cord)


## Instruction for use

## BLOOM! COLUMNS Ø 60 cm

### NOTE! USE ONLY 18 WATT MAX. ENERGY-SAVING LIGHT BULBS

To prevent heat from building up in the planter.

Do not touch the halogen bulbs while they are switched on. They are hot!



### Installation

You can use BLOOM! indoors as well as outdoors, as long as you use earthed wall sockets. The BLOOM! power cord must be led through the designated ducts. Make sure that BLOOM! is placed on a stable surface at ground level and not embedded in the ground. The same applies to the power cord. Please see 'permanent configuration' if you do want to conceal the cord.

### Replacing light bulb(s)

Always unplug BLOOM! before working on it.

1. Unplug BLOOM!
2. Unscrew the lid.
3. Replace the light bulb(s), using only **18 watt max. energy-saving light bulbs**
4. Screw the lid on tightly.
5. Put the plug into the socket again.

### Permanent configuration

If BLOOM! is permanently installed outdoors (for more than one year), BLOOM! should be fitted with a suitable outdoor underground cord by a certified electrician.

### Maintenance

Always unplug BLOOM! before carrying out maintenance work. If the power cord is damaged, it should be replaced immediately by the same type of cord with a moulded plug. Clean BLOOM! with a household cleaning agent in a low concentration. Do not use petrochemical solvents such as thinner, white spirit, etc.

### Technical specifications

Voltage	220-240V~ 50/60 Hz
Protection class	Class 1
Protection grade	IP44
Light bulbs	2 x E27 (large socket) 230V <b>18 watt max.</b> energy-saving light bulbs
Cord	H05RN-F 3x1.00 with moulded plug

### Dimensions:

Diameter	60 cm
Height	107 cm
Cord length	400 cm
Weight	± 20 kg (including light bulbs and cord)